FORMAT PROCEDURE FOR CMS H30-WS SUBSYSTEM

CMS H30-WS is a 30mb hard disk subsystem compatible with IBM PC/XT, Compaq Deskpro, AT&T 6300 and compatible computers using one of the following DOS versions: IBM DOS 3.1, 3.21, 3.3, Compaq DOS 3.2, AT&T DOS 3.1.

Controller jumper settings:

S1.....JUMPER ON 6
W8&W4.....2 AND 3 CLOSED
W3.....CLOSED
W6.....1 AND 2 CLOSED
W9.....OPEN

Low level format procedure:
Boot with a copy of DOS in drive "A" and type:

A>Debug <cr>	
-g=c800:5	
(The following will be displayed on the screen;)	
Current Drive is C; Select new Drive or RETURN for current	*<enter>*
Current interleave is 3, select new interleave or RETURN for current	*<enter>*
Are you dynamically configuring the drive-answer Y/N	*N <enter>*
Press "Y" to begin formatting drive C with interleave 3	Y <enter>
Formatting...	
Do you want to format bad tracks-answer Y/N	*N <enter>*
System will now restart. Insert DOS diskette in Drive A	
Press any key when ready.	

Partition and high level format procedure:

A>FDISK <cr>
Choose option 1 to create partition on the entire drive. The system will reboot now.

You are now ready for DOS format.

To format the hard drive, type:
A>Format c: /s/v <cr>

The CMS sub-system is now formatted with a capacity of 32 megabytes. You can now boot the system from drive "C".